

## Technical Specifications

<b>Power supply</b>	CR2450
<b>Interface</b>	Loxone Air: 868MHz (SRD Band Europe), 4 channels available 915MHz (ISM Band Region 2), 10 channels available max. Power 3.16mW
<b>Ambient temperature</b>	-20 ... 60°C / -4 ... 140°F
<b>Humidity</b>	max. 95% r.H. (non condensing)
<b>Touch points</b>	5 touch points, capacitive touch detection
<b>Click feedback</b>	Yes
<b>Temperature detection range</b>	-40 ... 125°C / -40 ... 257°F +/- 0.5°C / 0.9°F
<b>Humidity detection range</b>	0 ... 100% r.H. +/- 2% (non condensing)
<b>Safety rating</b>	IP40
<b>Dimensions</b>	80x80x10mm / 3.15x3.15x0.4" (LxWxH)
<b>Maintenance &amp; Cleaning</b>	This device is free of main- tenance and may only be cleaned with a dry cloth.

# LOXONE

## Need Help?

[loxone.com/support](https://loxone.com/support)

Loxone Electronics GmbH  
Smart Home 1  
4154 Kollerschlag  
Austria

[loxone.com](https://loxone.com)



VI20320

# LOXONE



## Touch Air

Part No: 100155 (White)  
Part No: 100180 (Anthracite)

## About the product

The Loxone Touch has five touch zones, which can be configured according to your needs. The large central touch zone is ideal for controlling lighting, whilst the corner zones are handy for controlling music and blinds.

## Features

- 5 touch buttons
- Temperature & humidity sensor
- Optional click feedback

## Installation

Install the mounting frame on the desired installation place. Power up the device with the provided battery and pair it with your Miniserver in Loxone Config. To finish the installation attach the Loxone Touch on the mounting frame.

## Information

Contains FCC ID: COR-ZWIR4512AC1

This device complies with part 15 of the FCC rules.

Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation.

This folder is a part of the product!



For additional information, declaration of conformity, visit [www.loxone.com/help/touch-air](http://www.loxone.com/help/touch-air)

